



dimensions of LEXIC modular din-rail equipment



	A	B					C	D	E	F	G
		1-pole	1-pole + N	2-pole	3-pole	4-pole					
Thermal-magnetic MCBs LR, DX, DX-H up to 63 A	70		17.7	35.6	53.4	71.2	60	83	44	76	94
DX-L, DX D curve, DX-H from 80 to 125 A	70	26.7		53.4	80.1	106.8	60	83	44	76	89
Motor MCBs	82.5			44.5			72.2	89	44	87.3	91
Earth leakage modules up to 63 A	70			35.6	53.4	71.2	60	93	44	76	99
from 80 to 125 A	70			71.1	107.2	107.2	60	88	44	76	89
RCBOs	70	17.7	35.6	71.2		124.6	60	83	44	76	94
4-pole RCBOs with 4 modules	70					71.2	60	83	44	76	94
RCDs (LR,DX)											
2-pole	70			35.6			60	83	44	76	94
4-pole	71.5					71.2	60	83	44	77.5	94
Fuse carriers	67	17.7	17.7	35.6	53.4	71.2	60	83	44	73	94
Auxiliary contacts Cat.Nos 073 50/51/52 Cat.No 073 54	70			8.7			60	83	44	76	83
	70			17.7			60	83	44	76	83
Control auxiliaries	70			17.7			60	83	44	76	83
Remote control Cat.No 073 73	74			54			74	83	44	80.5	89
STOP & GO	74			54			74	83	44	80.5	102
DX-IS remote trip head	72			35.5	53.5	71.5	60	83	44	78	94
Isolating switches 16 - 20 - 32 A	72	17.7		17.7	35.6	53.4	60	83	44	74	94
63 - 100 - 125 A	72	17.7		35.6	53.4	71.2	60	83	44	74	94
Changeover switches Cat.Nos 043 82/85 Cat.Nos 043 83/86	68			17.7			60	83	44	74	94
	68			35.6			60	83	44	74	94
Push-buttons/control switches	68			17.7			60	83	44	74	94
Indicators	63			17.7			60	83	44	69	94
Pulse operated latching relays	64	17.8		17.8		35.6	61	83	44	70	95
Light sensitive switches Cat.Nos 037 23/21 Cat.No 037 25	60			35.6			60	85	37.5	66	70
	60			88			60	84	37.5	66	70
Sockets outlets	60			44.5			60	83	44	66	92
Buzzers/bells	60			17.5			60	76	44	66	85
Time lag switch 047 02/04	60			17.8			60	94	44	66	94
Time delay relays	60			17.7			60	83	44	66	94
Remote control dimmers Cat.Nos 036 58/59/80 Cat.No 036 60 Cat.No 036 71	60			36			60	83	44	66	94
	60			72			60	83	44	66	94
	60			108			60	83	44	66	94
Voltage surge protectors 030 00 030 22/23 039 10 039 20 to 23 039 30 to 33 039 40/41/43 039 51 038 28/29	73	35.4					73	150	44	80	150
	64	35.6			106.8	142.4	64	90	44	71.5	97
	60			35.6	53.4	71.2	60	86	44	68	91
	60	17.7		35.6	53.4	71.2	60	86	44	68	91
	60	17.7		35.6	53.4	71.2	60	86	44	68	91
	60	17.7		35.6		71.2	60	86	44	68	91
	60	17.7		35.6			60	86	44	73	94
	60	17.7					60	86	44	68	91

Description	A	B	C	D	E	F
Programmable time switches 037 05 037 30/40/42/44 037 52/53/55 047 61/63/71 047 64/67 047 70	60	17.8	60	83	44	66
	60	17.8	60	83	44	66
	60	53	60	83	44	66
	60	35.6	60	83	44	66
	60	35.6	60	83	44	66
	60	90	60	83	44	66
Voltmeters - Ammeters	60	70	60	83	44	66
Contactors - 1 module 16 and 25 A	62	17.8	60	83	44	67.5
Contactors 25, 40 and 63 A 2 modules 3 modules	60	35.6	61	83	44	67
	60	54	61	83	44	67
Contactors 100 A 6 modules	60	90	60	83	44	66
Auxiliaries for contactors and pulse operated latching relays	60	9	60	83	44	66
Transformers and power supplies 042 10/30/31 042 25 042 37/41/52 042 54 042 91/92 042 95 to 98 042 93	60	72	60	83	44	66
	60	35.8	60	83.5	44	66
	60	71.5	60	83.5	44	66
	60	89	60	94	44	66
	60	105	60	95	44	66
	60	89	60	95	44	66
	60	70	60	95	44	66
Electrical energy metering 046 73/74 046 81/72	60	72	60	81	44	66
	60	35.5	60	89	44	66
Central measuring unit 046 65/67	64	105	64	89.5	44	69
Residual current relay 260 88	60	35.5	60	89	44	66