

48290163



Strong points

- Plug & Play
- Multi-circuit
- Compact
- Accurate
- MID certified (for S-xxxMID versions)

General characteristics

- 3 integrated current sensors
- Measurement up to 63 A
- Configurable as 3 single-phase circuits or 1 three-phase circuit

Compliance with standards

- IEC 61557-12
- UL 61010 Guide FTRZ/PICQ File E257746
- ANSI C12.20
- EN 50470-1
- EN 50470-3
- Directive 2014/32/EU

Access to resources (ex: manuals)

DIRIS Digiware S current acquisition modules have 3 integrated current sensors for the measurement of electrical circuits up to 63 A. Positioned directly above or below the protective devices, they are associated with the DIRIS Digiware U voltage measurement module to measure consumption, and to monitor the electrical installation and the quality of the power supply.

Technical Characteristics

Application	Metering
Model	S-130MID
Number of current inputs	3
Type	Current acquisition module
MID Certification	Yes

Classification

UNSPSC	83101808
ETIM Class	EC002301

Commerce

Effective date	2022-06-01
Offer Life Cycle Code	40
Country of origin	FR

Environmental Sustainability

PEP Filename	SOCO-00093-V01.01-EN.pdf
Climate change - Total - Cradle to Grave [kg CO ₂ eq.]	23
Climate change - Total - Cradle to Gate [kg CO ₂ eq.]	10

Logistics

GTIN/EAN	3596033199776
Customs number	9030337000
Weight of the packing unit [kg]	0,09
Length of the packing unit [m]	0,01
Width of the packing unit [m]	0,08
Depth of the packing unit [m]	0,035