



Casambi APP

Ligalicht

1.1	
1.2	
2.1	
2.2	

Casambi APP

On / Off  
menu option "All luminaires"  
selected

- 1.1
- 1.2
- 1.3
- 1.4
- 2.1
- 2.2
- 2.2
- 2.2
- 2.4

Casambi APP

On / Off  
menu option "All luminaires"  
not selected

- 1.1
- 1.2
- 1.3
- 1.4
- 2.1
- 2.2
- 2.2
- 2.2
- 2.4

Casambi APP

Impulse

- 1.1
- 1.2
- 1.3
- 1.4
- 2.1
- 2.2
- 2.3
- 2.4

Casambi APP

Impulse 1 sec.

- 1.1
- 1.2
- 1.3
- 1.4
- 2.1
- 2.2
- 2.3
- 2.4

Casambi APP

On / Off  
Impulse

- 1.1
- 1.2
- 1.3
- 1.4
- 2.1
- 2.2
- 2.3
- 2.4

1 APP for relays 1.1-1.4, 1 APP for relays 2.1-2.4  
When programming scenes, all 4 channels of one relays is always affected.  
Whereby the state 1 or 0 must be set.

Wiring Diagram: LIGA air module (profiled)  
Luminaire Model: ...  
Control: DIN-Module 2x4 Relay / 4 Button (230VAC) 10A ON / OFF / Divers

LIGA.AIR.2X4.REL.4.T.240

V1.3 / 11.07.2023



**LIGA AIR**

LICHTTEAM AG  
Stationsstrasse 89  
CH-6023 Rothenburg  
SWITZERLAND

+41 41 280 57 57  
mail@ligaair.ch  
www.ligaair.ch

